

## Fluxgate Closed Loop Current Sensor CYFGCS300HIT

CYFGCS300HIT is a current sensor based on the fluxgate closed-loop principle, and can be used for measuring DC, AC, pulse and various irregular waveform currents under galvanic isolation conditions.

The multi-point zero-flux technology is applied to existing high-precision DC sensor technology. By combining excitation flux closed-loop control, self-excitation flux gate technology, and multi-loop control, it achieves zero-flux closed-loop control of excitation flux, DC flux, and AC flux. Additionally, by establishing a high-frequency ripple sensing channel, it enables the detection of high-frequency ripple, thereby providing the sensor with high gain and measuring accuracy across the entire bandwidth.

### Core Technologies

- Closed-loop excitation flux control technology
- Self-excitation demagnetization technology
- Multi-point zero-flux technology
- Multi-range automatic switching technology
- Temperature compensation technology

### Performance Features


- Primary-to-secondary isolation measurement
- Excellent linearity and accuracy
- Extremely low temperature drift
- Extremely low zero drift
- Strong resistance to electromagnetic interference
- Wide bandwidth and fast response time

### Technical Data


Parameters	Symbol	Test Conditions	Values	Unit
Supply Voltage	$V_C$		$\pm 15(\pm 5\%)$	V
Rated input current DC	$I_{PN\_DC}$		$\pm 300$	A
Rated input current AC RMS	$I_{PN\_AC}$		212	A
Overload Current	$I_{PM}$	1 min	$1.2 \times I_{PN}$	A
Current to current ratio	$K_N$	Input : Output	3000 : 100	A/mA
Rated output current DC	$I_{OUT}$	Rated input current	$\pm 100$	mA
Measuring resistance	$R_M$		0 ~ 20	$\Omega$
Current consumption	$I_C$	Rated input current	$\pm(15\sim 35)+I_{OUT}$	mA
Linearity	$\epsilon_L$	Whole measuring range	<0.002	%
Accuracy ( $T_A=-40^\circ\text{C} \sim 85^\circ\text{C}$ )	X	DC input current	<0.02	%
Zero point offset current	$I_O$	$T_A=25^\circ\text{C}$	< $\pm 5$	$\mu\text{A}$
Thermal drift of offset current	$I_{OT}$	$T_A=-40^\circ\text{C} \sim 85^\circ\text{C}$	< $\pm 10$	$\mu\text{A}$
Following accuracy di/dt	di/dt		>100	A/ $\mu\text{s}$
Response time	$T_r$	di/dt=100A/ $\mu\text{s}$ , 90% $I_{PN}$	<1	$\mu\text{s}$
Bandwidth (-3dB)	F		DC~100	kHz
Operating temperature	$T_A$		-40~+85	$^\circ\text{C}$
Storage temperature	$T_S$		-55~+95	$^\circ\text{C}$
Relative humidity	RH		20-80	%
Mass	m		135 $\pm$ 10	g

### Safety Features

Parameters	Symbol	Test Conditions	Values	Unit
Isolation voltage	$V_d$	50Hz, 1min	5	kV
Transient isolation voltage	$V_w$	50 $\mu\text{s}$	10	kV
Creepage distance	dCp	Primary side to enclosure	32.3	mm
Electrical Clearance	dCi	Primary side to enclosure	24.5	mm
Comparative tracking index	CTI	IEC-60112	175	V





## Case Style and Connection



### Pin arrangement:

V+: +15V  
V-: -15V  
OUT:  $I_{OUT}$   
GND: 0V (power ground)



This product is an injection-molded part made of ABS+PC. Unless otherwise specified, its dimensions and mounting dimensions comply with GB/T 14486-2008 MT6.

### Operating Status Description


#### ◇ During normal operation, the green light remains on:

After the device is powered on, the green indicator light remains on when the device is functioning normally.

#### ◇ The green light turns off in case of current overload or power supply abnormalities:

If the green light is off, first check whether the sensor's power supply is functioning normally.

If the power supply is normal but the green indicator light is off, this indicates that the current sensor is in a non-zero flux state. If the bus input current exceeds the sensor's specified range at this point, the sensor enters overload mode, and the output current is no longer proportional to the input current signal. In overload mode, the sensor's output current remains at its maximum level, and the green indicator light turns off. Once



the input current returns to the specified measuring range, the sensor's output current returns to normal, and the green indicator light remains lit.

## Test Instructions

By measuring the output current  $I_{OUT}$  flowing through the  $R_M$ , or the voltage  $U_R$  across the measuring resistor  $R_M$ , the primary current  $I_P$  can be determined by:

$$I_P = K_N * I_{OUT} = K_N * (U_R / R_M)$$

## Application Note

1. Incorrect wiring may cause damage to the sensor. After the sensor is powered on, the same-phase voltage value can be measured at the output terminal when the measured current passes through the sensor in the direction of the arrow.
2. When taking measurements with the sensor, configure the measuring resistor according to the specifications in the data sheet. Additionally, ensure that the measuring resistor is securely connected to the sensor's output terminal to prevent an open circuit in the sensor output, which could cause product malfunction.
3. The sensor must be powered with two voltage supplies. The operating voltage of the power supplies must comply with the requirements, and the supply current for both the positive and negative terminals must be no less than the maximum power consumption current specified in this data sheet, with a margin of safety.
4. The temperature of the primary measuring wire or copper rod should not exceed 95°C.

## Application Areas

- Medical Equipment: Scanners, MRI
- Power: Converters, Inverters
- New Energy: Photovoltaics, Wind Power
- Automotive: Electric Vehicles
- Naval: Electric-powered Ships
- Aerospace: Satellites, Rockets
- Metrology: Verification and Calibration
- Rail Transit: High-speed Trains, Subways, Trams and Trolleys
- Test and measuring instruments: Power analyzers, high-precision power supplies
- Smart grid measurement: Power generation, battery monitoring, medium- and low-voltage substations
- Industrial control: Industrial motor drives, welding, robotics, cranes, elevators, ski lifts